

10/100M TX-FX Managed

100BASE-TX TO 100BASE-FX

Fast Ethernet Managed Media Converter



Features

| | |
|---------------------|--|
| Interface/Ports: | 1 x RJ-45, 1 X SC, ST or SFP |
| Connectivity: | Twisted Pair Fiber |
| Connectivity Media: | 10/100Base-TX Twisted Pair 100Base-FX (50/125 μ m, 62.5/125 μ m MMF) (9/125 μ m SMF) |
| Distance Supported: | 2km, 20km |
| Wavelength: | 1310nm, 1550nm |
| Network Technology: | 10/100Base-TX 100Base-FX |
| Status Indicators: | Power Copper Link Fiber Link Copper Receive activity Fiber Receive activity |
| Input Voltage: | 120V |
| Input Current: | 1A |
| Temperature: | 32°F (0°C) ~ 122°F (50°C) |
| Humidity: | 5 ~ 90% Non-condensing |

Product Description

The AddOn line of products is a complete offering of Managed Fiber Media Converter. 10/100M TX- FX Managed Media Converter functions including variety of data rate, SM/MM, single fiber and double fiber etc. with simple set-up. Real time remote manageable fiber media converter. AddOn Media Converters and Network Interface Cards are 100% compliant for all of our networking needs.

ADD-MFMC-FX-ST

Managed Media Converter 100BFX
10/100M 1310NM MMF ST 2km Reach

ADD-MFMC-LX-2ST

Managed Media Converter 100BLX
10/100M 1310NM SMF ST 20km Reach

ADD-MFMC-BX-UST

Managed Media Converter 100BXU
1310/1550NM BiDi SMF ST 20km Reach

ADD-MFMC-BX-DST

Managed Media Converter 100BXD
1550/1310NM BiDi SMF ST 20km Reach

ADD-MFMC-SFP*

Managed Media Converter 100M
10/100M with open SFP port

ADD-MFMC-FX-SC

Managed Media Converter 100BFX
10/100M 1310NM MMF SC 2km Reach

ADD-MFMC-LX-2SC

Managed Media Converter 100BLX
10/100M 1310NM SMF SC 20km Reach

ADD-MFMC-BX-USC

Managed Media Converter 100BXU
1310/1550NM BiDi SMF SC 20km Reach

ADD-MFMC-BX-DSC

Managed Media Converter 100BXD
1550/1310NM BiDi SMF SC 20km Reach

*For complete list of SFP/XFP module
please visit www.addoncomputer.com